

YI1000 Series



MOTOR INTEGRATED VARIABLE SPEED DRIVE

- IP65, High Protection Level
- No Need For Electrical Cabinet
- Integrated Drive-Train Solution



Specifications

YI1000 Series

Items		YI1000
Power Supply	Rated voltage, Frequency	1PH AC 220V 50/60Hz
	Voltage Range	220V: 170V ~ 240V
Output	Voltage Range	220V: 0V ~ 220V
	Frequency Range	0.10~400.00Hz
Control method		V/F control
Indication		Operating status/Alarm definition/interactive guidance: eg, frequency setting, the output frequency/current, DC bus voltage, the temperature and so on.
Control Specifications	Output Frequency Range	0.10Hz~400.00Hz
	Frequency Setting Resolution	Digital input : 0.1 Hz, analog input: 0.1% of maximum output frequency
	Output Frequency Accuracy	0.1Hz
	V/F Control	Setting V/F curve to satisfy various load requirements.
	Torque Control	Manual increase:enable to set 0.0~20.0% of raising torque.
	Multifunctional Input Terminal	3 multi-function input terminals, realizing functions including fifteen section speed control, program running, four-section acceleration/deceleration speed switch, UP/DOWN function and emergency stop and other functions
	Multifunctional Output Terminal	2 multi-function output terminals for displaying of running, zerospeed, counter, external abnormality, program operation and other information and warnings.
	Acceleration/ deceleration Time Setting	0~999.9s acceleration/deceleration time can be set individually.
Other Functions	PID Control	Built-in PID control
	RS485	Standard RS485 communication function (MODBUS)
	Frequency Setting	Analog input:0 to 10V, 4 to 20mA can be selected; Digital input: Input using the setting dial of the operation panel or RS485or UP/DOWN. Note: AVI terminals can be used to select an analog voltage input (0-10V) and analog current input (4-20mA) through the switch
	Multi-speed	Three multifunction input terminals, 8 section speed can be set
	Automatic voltage regulation	Automatic voltage regulation function can be selected
	Aux. Power Supply	24V Power Supply for external devices and sensors etc.
Protection/ Warning Function	Overload	150%, 60second (Constant torque)
	Over Voltage	Over voltage protection can be set.
	Under Voltage	Under voltage protection can be set.
	Other Protections	Output shortcircuit, over current, and parameter lock and so on.
Environment	Ambient Temperature	-10℃ to 40℃ (non-freezing)
	Ambient Humidity	Max. 95% (non-condensing)
	Altitude	Lower than 1000m
	Vibration	Max. 0.5G
Structure	Cooling Mode	Air Cooling
	Protective Structure	IP 65
Installation	Mode	Motor Integrated